


Non-isolated DC-DC converter

1.8W Fixed input voltage and dual regulated output



### **FEATURES**

- Ultra-small size: 46.00 x 25.70 x 15.50mm
- ±3000 VDC dual independent adjustable output
- High output voltage stability, low-time drift, low-temperature drift
- Operating ambient temperature range: -40℃ to +85℃
- Output short circuit and over-current protection
- EMI meets CISPR32/EN55032 CLASS B
- Electrical safety distances comply with IPC standards





HO1-PN302V-0.3C offers output power 1.8W, it features with operating ambient temperature range -40°C to +85°C, output short circuit protection, over-current protection, ultra-small size packaging, ±3000 VDC dual independent adjustable output, high output voltage stability, low time drift, temperature drift, low ripple, which are specifically designed for applications in board power systems where high voltages are required and output ripple requirements are high and output voltage stability is critical. Products are widely applicable: Ion mobility spectrum, mass spectrum, light spectrum, electron beam, ion beam and other high pressure applications.

Selection Guide								
0 - 44644	Part No.	Input Voltage (VDC)	Input Current <sup>®</sup> (mA) Full load/No-load		Output Voltage (VDC)			Current (mA)
Certification		Nominal (Range)	Тур.	Max.	Nominal <sup>®</sup>	Range	Guaranteed range	Max./Min.
	HO1-PN302V-0.3C	12 (10.8-13.2)	340/80	360/110	±3000	0 to ±3000	+300 to +3000 -300 to -3000	0.3/0

Note:

- ① At the nominal input voltage and nominal output voltage;
- @ When the Vadj control voltage is equal to 5VDC (Typ.), The relationship curve between output voltage and control voltage is shown in Fig.3.

Input Specifications					
Item	Operating Conditions	Min.	Тур.	Max.	Unit
Surge Voltage (1sec. max.)				18	VDC
Input Filter Type			PI fi	lter	
Hot Plug		Unavailable			

Operating Conditions	Min.	Тур.	Max.	Unit	
rence Voltage accuracy 0%-100% load, reference 5.15V output		±1	±2		
		±1	±2	0/	
		±0.05	±0.1	%	
		±0.05	±0.1		
Time Coefficient  Nominal input voltage, nominal output voltage, full load, after warming up for 30 minutes		±0.003	±0.005	%/Hr	
efficient Nominal input voltage, nominal output voltage, full load		±0.003	±0.05	%/℃	
20MHz bandwidth, nominal input voltage, 0%-100% load	-	300	400		
20MHz bandwidth, nominal input voltage 0%-100% load External RC filter ( see Fig.2 )		50	100	mVp-p	
	110	130	150	%lo	
Short-circuit Protection Input voltage range		Constant current mode, continuous, self-recovery			
	Output voltage guaranteed range, see Fig.3  0% -100% load, reference 5.15V output  Input voltage range, nominal output voltage, full load  Nominal input voltage, nominal output voltage, 10%-100% load  Nominal input voltage, nominal output voltage, full load, after warming up for 30 minutes  Nominal input voltage, nominal output voltage, full load  20MHz bandwidth, nominal input voltage, 0%-100% load  20MHz bandwidth, nominal input voltage  0%-100% load  External RC filter ( see Fig.2 )	Output voltage guaranteed range, see Fig.3	Output voltage guaranteed range, see Fig.3 - ±1  0% -100% load, reference 5.15V output - ±1  Input voltage range, nominal output voltage, full load - ±0.05  Nominal input voltage, nominal output voltage, 10%-100% load - ±0.05  Nominal input voltage, nominal output voltage, full load, after warming up for 30 minutes - ±0.003  Nominal input voltage, nominal output voltage, full load - ±0.003  20MHz bandwidth, nominal input voltage, 0%-100% load - 300  20MHz bandwidth, nominal input voltage 0%-100% load - 50  External RC filter ( see Fig.2 )  110 130  Constant current in	Output voltage guaranteed range, see Fig.3 - ±1 ±2  0% -100% load, reference 5.15V output - ±1 ±2  Input voltage range, nominal output voltage, full load - ±0.05 ±0.1  Nominal input voltage, nominal output voltage, 10%-100% load - ±0.05 ±0.1  Nominal input voltage, nominal output voltage, full load, after warming up for 30 minutes  Nominal input voltage, nominal output voltage, full load - ±0.003 ±0.005  20MHz bandwidth, nominal input voltage, 0%-100% load - 300 400  20MHz bandwidth, nominal input voltage 0%-100% load - 50 100  External RC filter (see Fig.2)	

**MORNSUN®** 


MORNSUN Guangzhou Science & Technology Co., Ltd.

General Specifications					
Item	Operating Conditions	Min.	Тур.	Max.	Unit
Operating Temperature	See Fig.1	-40		+85	· °C
Storage Temperature		-40		+85	
Storage Humidity	Non-condensing	5	-	85	%RH
Pin Soldering Resistance Temperature	Soldering spot is 1.5mm away from case for 10 seconds			300	°C
Vibration 10-150Hz, 5G, 0.75mr			nm. along X	, Y and Z	
Switching Frequency	Nominal input voltage, full load		83	-	kHz
MTBF	MIL-HDBK-217F@25°C	1000	-	-	k hours

Mechanical Specifications			
Housing Material Black flame retardant heat-resistant plastic(UL94 V-0)			
Dimensions	46.00 x 25.70 x 15.50mm		
Weight 31g (Typ.)			
Cooling Method	Free air convection		

Electromagnetic Compatibility (EMC)				
Emissions	CE	CISPR32/EN55032	CLASS B (see Fig.5-1) for recommended circuit)	
	RE	CISPR32/EN55032	CLASS B (Without extra components)	
	ESD	IEC/EN61000-4-2	Contact ±4kV	perf. Criteria B
Immunity	RS	IEC/EN61000-4-3	10V/m	perf. Criteria B
	EFT	IEC/EN61000-4-4	100kHz ±2kV (see Fig.5-2) for recommended circuit)	perf. Criteria B
	Surge	IEC/EN61000-4-5	line to line ±2kV (see Fig.5-2) for recommended circuit)	perf. Criteria B
	CS	IEC/EN61000-4-6	3 Vr.m.s	perf. Criteria B


# **Product Characteristic Curve**




### Design Reference

### 1. Typical application

This series are tested according to the test circuit recommended in Fig.4 before leaving the factory. To futher reduce the output ripple as required, an external RC filter can be connected to the output as shown in Fig.2





Cin	100µF/25V Aluminium electrolytic capacitor	
R1/R2	<b>2k</b> Ω	
C1/C2	15nF/4000V	
RO	Adjustable resistance ≥10kΩ	





Fig.2



(Note: 100% Vadj is equal to 5VDC (Typ.))
Fig. 3 The relationship curve of output voltage and control voltage

### 2. Ripple and noise test recommended circuit

# Vin • Vin +HV• • Vadj High Voltage power supply • Vref • GND • HV•


Fig.4 Ripple and noise test recommended circuit

### Parameter description:

Cin	100µF/25V Aluminium electrolytic capacitor
R1/R2	$1k\Omega/2W$ resistance
C1/C2	472K/250VAC Y2 capacitance
R0	Adjustable resistance $\geq 10$ k $\Omega$



### 3. EMC compliance circuit





### Parameter description:

C0/C3	680µF/25V Aluminium electrolytic capacitor
C1/C2	22uF/25V
LDM1	12uH
RO	Adjustable resistance $\geq 10$ k $\Omega$


4. For additional information please refer to DC-DC converter application notes on www.mornsun-power.com

## Dimensions and Recommended Layout





THIRD ANGLE PROJECTION 🕁 📢



Note: Grid 2.54\*2.54mm

Pin-Out					
Pin	Mark				
1	Vin				
2	GND				
3	Vadj				
4	Vref				
5	+HV				
6	-HV				



### Notes:

- 1. For additional information please refer to Product Packaging Information. Packaging bag number: 58220011;
- If the product is not operated within the required load range, the product performance cannot be guaranteed to comply with all parameters in the datasheet;
- 3. Unless otherwise specified, parameters in this datasheet were measured under the conditions of Ta=25°C, humidity<75%RH with nominal input voltage and rated output load;
- 4. All index testing methods in this datasheet are based on our company corporate standards;
- 5. We can provide product customization service;
- 6. Products are related to laws and regulations: see "Features" and "EMC";
- 7. Our products shall be classified according to ISO14001 and related environmental laws and regulations, and shall be handled by qualified units.

# Mornsun Guangzhou Science & Technology Co., Ltd.

Address: No. 5, Kehui St. 1, Kehui Development Center, Science Ave., Guangzhou Science City, Huangpu District, Guangzhou, P. R. China Tel: 86-20-38601850 Fax: 86-20-38601272 E-mail: info@mornsun.cn www.mornsun-power.com

**MORNSUN®** 

MORNSUN Guangzhou Science & Technology Co., Ltd.